

ACADEMY | SYSTEM SPECIFICATIONS

6021 Hollywood Blvd, Los Angeles, CA 90028

Updated: June 2018

AUDIO

Audio Control

1 - NST	Audio D48S Processor
1 - BSS	Blu160 DSP London Architect Ver6.05
1 - Midas	M32 (FOH Audio Console)

PA System

4 - Funktion One	VERO V90 - 10" + 1.4" Compression Driver Mid/High (2 per side)
4 - Funktion One	VERO V315 - Triple 15" Low/Mid Cabinets (2 per side)
12 - Funktion One	F218 2x 18" Sub-woofers
1 - NST	Audio D48S Processor
1 - BSS	Blu160 DSP London Architect Ver6.05
4 - MC ²	E-45 2 Channel Amplifier Per Ch: 2500W @4Ω 4,200W @2Ω
2 - Linea Research	44M20 4 Channel Amplifier Per Ch: 3000W @4Ω 5,000W @2Ω

DJ BACKLINE

Must request Qty	Pioneer	CDJ 2000 Nexus 1&2
Must request Qty	Pioneer	DJM900 Nexus 1&2, DJM 2000
Must request Qty	Pioneer	EFX 1000 & RMX 1000
Must request Qty	Allen&Heath	Zone92 & DB4
Must request Qty	Technic	1200 Turntables

Main Stage DJ Monitors

2 - FunktionOne	PSM318-H (1 per-side)
2 - FunktionOne	PSM318-L (1 per-side)
1 - MC ²	t-2000
1 - MC ²	e-100

LIGHTING Fixture plot and patch sheet available on request.

Light Control

GrandMA Series 2 LITE
Madrix Software (Pixel Bars)
Enttec Storm 24 (ArtNet to DMX node) Signal Distribution

Special Effects

4 - Liquid Nitrogen Jets
1 - Base Hazer with water-based fluid
2 - 10 watt RGB Lasers

Fixtures

8 - Elation Platinum Spots
32 - Elation Platinum Beam 5R
10 - Martin Atomic 3k
162 - Elation Pixel Bars
4 - LED Pars (Stage Wash)

VIDEO Pixel map and mask available on request.

Video Control

Resolume Arena 6
Output Resolution: 1920x1080

Side Wall LED

Oracle TR-16 16mm
48 Total Panels (per side)
Positioned along the Walls Left and Right (2x24)

Ceiling LED

Oracle TR-16 16mm 481 Total Panels
Positioned Along the ceiling in 5 rows
(2x37) (3x37) (3x37) (3x37) (2x37)

DJ Booth LED

Oracle Black widow 9mm
12 Total Panels
Positioned in front of DJ Booth (2x6)

LOADING

Elephant door: 7'w X 7'h
No Elevators